

Optimal population transfers in a quantum system for large transfer time

Symeon Grivopoulos
symeon@engr.ucsb.edu

Bassam Bamieh
bamieh@engr.ucsb.edu

February 1, 2008

Department of Mechanical and Environmental Engineering
University of California, Santa Barbara, CA 93106-5070

Abstract

Transferring the state of a quantum system to a given distribution of populations is an important problem with applications to Quantum Chemistry and Atomic Physics. In this work we consider exact population transfers that minimize the L^2 norm of the control which is typically the amplitude of an electromagnetic field. This problem is analytically and numerically challenging. Except for few exactly solvable cases, there is no general understanding of the nature of optimal controls and trajectories. We find that by examining the limit of large transfer times, we can uncover such general properties. In particular, for transfer times large with respect to the time scale of the free dynamics of the quantum system, the optimal control is a sum of components, each being a Bohr frequency sinusoid modulated by a slow amplitude, i.e. a profile that changes considerably only on the scale of the transfer time. Moreover, we show that the optimal trajectory follows a “mean” evolution modulated by the fast free dynamics of the system. The calculation of the “mean” optimal trajectory and the slow control profiles is done via an “averaged” two-point boundary value problem which we derive and which is much easier to solve than the one expressing the necessary conditions for optimality of the original optimal transfer problem.

1 Introduction

Steering a quantum system from its initial state to a given final state or a set of final states is one of the central problems in the control of such systems. While transfers to specific final states are very important for applications to Quantum Computing and Quantum Chemistry, transfers to given final populations are also important for many applications to Quantum Chemistry and Atomic Physics. Optimal Control is a natural approach to transfer problems: Frequently, one desires to optimize some aspect of the transfer. For example,

minimize the transfer time [1, 2], maximize some measure of efficiency of the control in achieving its objective [3] or minimize some measure of the size of the control, for instance its L^2 norm [4, 5, 6, 7]. Moreover, the optimal control(s), singled out of all possible controls that achieve the objective, should have interesting properties tied to the structure of the given system.

In this work we consider exact population transfers that minimize the L^2 norm of the control. We work in the semiclassical approximation, where the control field influencing the quantum system is taken to be a classical source. We also employ the dipole moment approximation, valid for long wavelength fields, where the spatial features of the system-control field interaction are lumped in an interaction Hamiltonian and the amplitude of the field becomes the control parameter. The dynamics of the system is given then by the time-dependent Schrodinger equation (we consider a system with one control - which is usually the case - and set $\hbar$ to 1):

$$i\dot{\psi} = (H_0 + V u(t))\psi. \quad (1)$$

We wish to find a $u \in L^2([0, T])$, that minimizes

$$\|u\|_{L^2([0, T])}^2 = \int_0^T u^2(t) dt, \quad (2)$$

and drives an initial state ψ_0 of system (1) to a target population distribution $\{|\psi_i(T)|^2 = p_i, i = 1, \dots, N\}$ (N is the dimension of the system and $\psi = \sum_i \psi_i e_i$, where the e_i 's are the orthonormal eigenvectors of H_0). This cost has been used extensively in the literature of optimal control of quantum systems. It provides a measure of the energy spent to create the controlling field and leads, as we will see, to interesting conclusions.

Relatively little work has been done on this problem. Analytically, it is a hard problem and explicit solutions are known only in few cases: In [4, 6] this is done for transfers between eigenstates in a two-dimensional system with two controls and in [5, 6] it is done for transfers between eigenstates of a three-dimensional system with four controls. In fact, both cases mentioned above are instances of a certain algebraic structure being present (the so-called $K + P$ structure) [5, 8], that allows one to find analytic expressions for the control and the state in terms of the unknown initial costate but the analytic determination of this unknown initial costate (and hence the complete solution of the problem) is possible only for systems of small dimensionality because one needs to analytically compute matrix exponentials and solve transcendental equations. In any event, this structure is special and will not be present in general. In another case [4] (for a two-state system with one control), it is possible to find an analytic expression for the control (in terms of unknown constants) but not for the state and so the problem has to be solved numerically from that point on. For higher dimensional systems, no general properties of the optimal control and state trajectory are known.

Numerically, the two-point boundary value problem that expresses the necessary conditions of optimality becomes increasingly harder to solve as the dimension of the system or the transfer time grows. Dimension growth dramatically

increases the computational cost of the numerical solution. More relevant to our work is the issue of large transfer time. In many typical applications, the transfer time may be a few orders of magnitude larger than the time scale of the free evolution of the system. This may be necessary for the transfer to be possible or for the amplitude of the control to be within experimentally feasible limits. The problem here is the presence of two time scales in the solution, i.e. stiffness: There is the fast time scale of the free dynamics of the quantum system and the slow time scale of the transition (which is of the order of T). This creates the need for a very detailed numerical solution in order to guarantee good solution accuracy resulting in large computational times. In applications one usually considers relaxations of this optimal transfer problem where one abandons the requirement for *exact* transfers and tries to minimize a combination of the integral cost (2) and a measure of distance from the desired final state or population distribution such as

$$a \int_0^T u^2(t) dt + \sum_{i=1}^N (|\psi_i(T)|^2 - p_i)^2, \quad (3)$$

($a \geq 0$). An advantage of optimal transfer problems like these over the one we are considering in this work is that they lead to two-point boundary value problems with separated boundary conditions and are amenable to iterative solution methods, see for example [9, 10, 11]. Yet, the above remarks hold for these as well. We shall comment on the connections between this work and the later type of optimal transfer problems in section 7.

We found that the study of optimal population transfers for large transfer times offers some insight into the nature of optimal control and state trajectory as well as computational advantages in the numerical solution of the problem. The main conclusions of our work are the following:

1. For generic population transfers and large enough transfer times, the optimal control has the following, physically plausible form: It is a sum of sinusoids with frequencies equal to the Bohr frequencies of the quantum system multiplied by slowly varying profiles, that is functions of $\frac{t}{T}$:

$$\begin{aligned} u_{opt}(t) &= \frac{i}{T} \text{tr} \left(e^{iH_0 t} V e^{-iH_0 t} L \left(\frac{t}{T} \right) \right) + O\left(\frac{1}{T^2}\right) \\ &= \frac{i}{T} \sum_{k \neq l} V_{kl} e^{i\omega_{kl} t} L_{lk} \left(\frac{t}{T} \right) + O\left(\frac{1}{T^2}\right). \end{aligned}$$

L is an anti-Hermitian matrix with zeros on the diagonal, whose entries are the profiles. This form is explicitly verified in all analytically solvable cases (where, because of the structure of the systems, there are no $O(\frac{1}{T^2})$ corrections) and it is in fact observed in numerical solutions.

2. Again for generic population transfers and large enough transfer times, the optimal trajectories follow a slow “mean” evolution upon which small deviations are imposed. The slow mean evolution and the slow control

profiles can be calculated by solving an “averaged” two-point boundary value problem (the term will be explained in section 3) in the fixed interval $[0, 1]$, irrespective of how large the transfer time T is. The small deviations of the optimal trajectories from their mean evolution are due to the free dynamics. Quantitatively,

$$\psi(t) = e^{-iH_0 t} \bar{\psi}\left(\frac{t}{T}\right) + O\left(\frac{1}{T}\right),$$

where $\bar{\psi}$ denotes the “mean trajectory” and the oscillatory $e^{-iH_0 t}$ term is responsible for the deviations from the mean evolution. There are also additional corrections, of higher order in a $\frac{1}{T}$ expansion.

Although these results hold for large transfer times, one may use a solution of the optimal control problem obtained this way for a large transfer time T as the first step in a continuation method solution of the original optimization problem where the continuation parameter is the transfer time. The point is that the large transfer time limit both reveals the structure of the controls and serves as a good starting point for the solution of the problem: Indeed, the associated “averaged” two-point boundary value problem in $[0, 1]$ is much easier to solve numerically than the original problem.

Our presentation is organized as follows: In section 2, we set up the optimal population transfer problem for a finite dimensional quantum system, review approaches to its solution and comment on the difficulties associated with these approaches. In section 3, we consider the quantum system with a certain class of controls and show how, for large transfer times T , it is approximated to first order in a $\frac{1}{T}$ perturbation expansion by an “averaged” control system. Then, we set up an optimal population transfer problem for this averaged system. Section 4 contains our main result, namely that, for large transfer time, the solution to the original optimal control problem is approximated by the solution of the optimal population transfer problem for the averaged system. This implies that the optimal control for the original problem belongs to the class of controls used to transform the original system to the averaged one and this provides a useful characterization of it. The proof of this result is contained in section 5. We demonstrate our approach with some examples in section 6. Section 7 concludes.

2 Optimal population transfers

In this section we derive the necessary conditions of optimality for the optimal population transfer problem described in section 1. We consider a quantum system influenced by an external, classical source (for example the electric field of a laser). For simplicity, we consider a system with one control (which is usually the case) and set $\hbar$ to 1 in Schrodinger’s equation:

$$i\dot{\psi} = (H_0 + V u(t))\psi.$$

Nevertheless, everything we do in this and the following sections can readily be generalized to systems with more controls.

Before we consider the optimal control problem, we want to address the controllability question for this system. The system (1) is controllable if, for every pair of initial and target states (ψ_0, ψ_d) there exists a transfer time T and a measurable $u(t)$, $t \in [0, T]$, such that the solution of (1) with $u(t)$ and $\psi(0) = e^{i\varphi_0} \psi_0$ results into $\psi(T) = e^{i\varphi_d} \psi_d$, for some $\varphi_0, \varphi_d \in S^1$. (In Quantum Mechanics all states are defined modulo a total phase. From (1) it is obvious that one may always set $\varphi_0 = 0$, for example.) Sufficiency conditions for controllability [12, 13, 14] are based on the classical results [15, 16, 17]. In this work, we would like to assume a somewhat strong form of controllability assumption as given, for example, in [13]. To state it, we need a few simple notions: A quantum system whose energy levels (eigenvalues of H_0) are all different from each other is called non-degenerate. Moreover, a system such that no two Bohr frequencies (differences of energy levels) are the same, is said to have no degenerate transitions. The connectivity graph $\mathcal{G}_M$ of a Hermitian matrix $M = (M_{ij})$ is defined as the pair $(\mathcal{N}_M, \mathcal{C}_M)$, where $\mathcal{N}_M = \{1, \dots, N\}$ is the set of nodes and $\mathcal{C}_M = \{(i, j), i > j, |M_{ij}| \neq 0\}$ is the set of edges joining the nodes. The graph $\mathcal{G}_M$ is called connected when there exists a path joining every two nodes.

Controllability assumption: The system (1) is non-degenerate, has no degenerate transitions and the graph of V is connected.

Then [13], (1) is controllable. As a matter of fact, this is the generic situation for controllability of (1).

We now proceed with the set up of the optimal control problem. We wish to find a $u \in L^2([0, T])$, that minimizes

$$\|u\|_{L^2([0, T])}^2 = \int_0^T u^2(t) dt,$$

and drives an initial state ψ_0 of system (1) to a target population distribution $\{|\psi_i(T)|^2 = p_i, i = 1, \dots, N\}$ (N is the dimension of the system). We will refer to this as optimal transfer problem (I). The Maximum Principle of optimal control [18, 19] provides necessary conditions for optimality in terms of the Hamiltonian function

$$H(\psi, \lambda, u) = \frac{1}{2}u^2 - i\lambda^*(H_0 + V u)\psi + i\psi^*(H_0 + V u)\lambda,$$

where $\lambda \in \mathbb{C}^n$ is the co-state vector. It is shown in Appendix A that solutions of the optimal control problem satisfy, $\lambda^*(t) \psi(t) = 0$.

The optimal control u and the corresponding state and co-state satisfy the equations

$$\dot{\psi} = \frac{\partial H}{\partial \lambda^*}, \quad \dot{\lambda} = -\frac{\partial H}{\partial \psi^*} \quad \text{and} \quad \frac{\partial H}{\partial u} = 0,$$

which, given the expression for H , have the form

$$i\dot{\psi} = (H_0 + V u)\psi, \quad (4)$$

$$i\dot{\lambda} = (H_0 + V u)\lambda, \quad (5)$$

$$u = i(\lambda^* V \psi - \psi^* V \lambda). \quad (6)$$

For convenience, we rewrite equations (4) and (5) using u from (6):

$$i\dot{\psi} = H_0 \psi + i(\lambda^* V \psi - \psi^* V \lambda) V \psi, \quad (7)$$

$$i\dot{\lambda} = H_0 \lambda + i(\lambda^* V \psi - \psi^* V \lambda) V \lambda. \quad (8)$$

To these equations one must append the boundary conditions

$$\psi(0) = \psi_0, \quad |\psi_i(T)|^2 = p_i, \quad \text{Im}(\psi_i^*(T) \lambda_i(T)) = 0, \quad (9)$$

$\forall i = 1, \dots, N$. The last of these equations are the transversality conditions at the endpoint. Their proof is also given in Appendix A. We will refer to the two-point boundary value problem comprised of equations (7) - (9) as two-point boundary value problem (I).

We briefly discuss now methods for its solution. Analytically, we may proceed as follows: Define the traceless, anti-Hermitian matrix Λ by $\Lambda := \psi \lambda^* - \lambda \psi^*$ and using (4) and (5) we can show that

$$\dot{\Lambda} = -i[H_0 + V u, \Lambda] = [-iH_0 + \text{tr}(V \Lambda) V, \Lambda] \quad (10)$$

where we substituted

$$u = i(\lambda^* V \psi - \psi^* V \lambda) = i \text{tr}(V \Lambda),$$

from (6). If we solve (10) analytically, we obtain an expression for the control function $u(t)$ in terms of unknown constants (these unknown constants are matrix elements of $\Lambda(0) = \psi(0) \lambda^*(0) - \lambda(0) \psi^*(0)$ and $\lambda(0)$ is what we are after). Then, one may attempt to solve (4) and (5) using this expression for u and determine these constants by satisfying the boundary conditions (9). In practice this program seems impossible to carry out in its entirety except for the few special cases mentioned in the introduction.¹ Numerically, one may attempt to solve the two-point boundary value problem (7) - (9) using, for example, some shooting or finite-difference method. This works for systems of small dimensionality and small transfer times but becomes increasingly harder as the system dimension grows and as larger transfer times are required for the transfer to be possible. As mentioned in the introduction, in many typical applications the transfer time has to be a few orders of magnitude larger than the time scale of

¹In all these works, and in fact in most of the literature of Geometric Control Theory, authors look at the “lifting” of the system $i\hbar \dot{\psi} = (H_0 + \sum_{\alpha} V_{\alpha} u_{\alpha}(t)) \psi$ to $SU(N)$, $i\hbar \dot{U} = (H_0 + \sum_{\alpha} V_{\alpha} u_{\alpha}(t)) U$ where the state transition matrix $U(t)$ is defined by $\psi(t) = U(t) \psi(0)$. It turns out that the formulation of the optimal control problem in the two setups is similar and in fact, equation (10) in that context is the co-state equation “pulled-back” on the cotangent space at the identity of $SU(N)$, see [17, 18].

the free dynamics of the system in order to achieve the desired transfer. Because the free dynamics of the system is oscillatory, the first terms on the right sides of equations (7) and (8) create small oscillations of the populations around their “mean” evolution towards their final values. This creates the need for a very detailed numerical solution in order to guarantee good solution accuracy. Examples of this can be seen in the graphs of section 6. Besides the usual unfavorable scaling of the solution efficiency with dimension (an issue which we do not address), this is the main source of difficulty of the problem. Note that these remarks are quite general and independent of the specific numerical methods used to solve the two-point boundary value problem. We will see in the following how this problem can be overcome.

Before we leave this section we would like to point out that our discussion so far, as well as in the following, will only concern *normal* extrema of the optimization problem (I). *Abnormal* extrema [20, 18] will not be considered. The reason is that the form of the abnormal extrema does not depend on the exact cost used in the minimization problem, and thus, the same abnormal extremum can be a local or even a global minimizer to many different cost functionals. In this sense, abnormal minimizers are not particular to one optimal control problem and don’t reflect its particular structure. So, in this work, all the discussion and results concern normal minima of problem (I) (as well as problem (II) to be defined in the next section).

3 Optimal population transfers for an averaged system

In this section, we introduce a special form for the control in equation (1), a sum of sinusoids with frequencies equal to the Bohr frequencies of the quantum system multiplied by slowly varying profiles, that is functions of $\frac{t}{T}$. We then proceed to “average out” the dynamics in the time scale of the free evolution of the system (this time scale is set by the Bohr frequencies), which is fast compared to the transfer time T . This leaves us with an “averaged” control system whose evolution approximates that of the original under the special form of the control introduced. The motivation for this lies in the following: We set up a corresponding optimal transfer problem for the averaged system, whose cost approximates the cost (2). We will show in section 5 how solutions to this optimal transfer problem approximate solutions to our original optimal transfer problem (I), to first order in an $O(\frac{1}{T})$ expansion, proving the results described in the introduction. We begin with the change of variable

$$x = e^{iH_0 t} \psi \tag{11}$$

in (1). In Physics, this is referred to as “transforming to the Interaction Picture”. The time evolution of the new variable x is due entirely to the control, because the free evolution has been accounted for. In terms of the new variable, (1) becomes

$$i\dot{x} = u F(t)x, \tag{12}$$

where,

$$F(t) := e^{iH_0 t} V e^{-iH_0 t}. \quad (13)$$

Note the appearance of the Bohr frequencies in the matrix elements of F ,

$$F_{ij}(t) = V_{ij} e^{i(E_i - E_j)t} = V_{ij} e^{i\omega_{ij}t}.$$

We adopt the following form for the control $u(t)$:

$$u(t) = \varepsilon(u_0(\varepsilon t) + \sum_{i \neq j}^N e^{i\omega_{ij}t} u_{ji}(\varepsilon t)), \quad (14)$$

where $u_{ji}^* = u_{ij}$ and u_0 is real, so that u is real. u_{ji} is a complex “envelope” that multiplies a sinusoid with frequency equal to the Bohr frequency for the transition i to j . The value of ε will be given shortly. We introduce $u(t)$ from (14) in (12) and rewrite (12) in component form:

$$i\dot{x}_i = \varepsilon(u_0(\varepsilon t) + \sum_{k \neq l} e^{i\omega_{kl}t} u_{lk}(\varepsilon t)) \sum_j e^{i\omega_{ij}t} V_{ij} x_j. \quad (15)$$

We approximate (15) for small ε using averaging. In averaging, one considers equations of the form

$$\dot{w} = \varepsilon f(w, t, \varepsilon), \quad (16)$$

where f must be a bounded C^2 function of its arguments with bounded derivatives up to 2nd order such that the limit

$$f_{av}(w) := \lim_{\tau \rightarrow \infty} \frac{1}{\tau} \int_t^{t+\tau} f(t', w, 0) dt'$$

exists. A standard averaging theorem (see Chapter 8 of [21]) guarantees that, for sufficiently small ε , the solution of

$$\dot{\bar{w}} = \varepsilon f_{av}(\bar{w})$$

with an initial condition $O(\varepsilon)$ close to the initial condition of (16) (i.e. $\bar{w}(0) - w(0) = O(\varepsilon)$) is $O(\varepsilon)$ close to that of (16) for a time interval of length $O(\frac{1}{\varepsilon})$. Equation (15) involves two time scales, 1 and $\frac{1}{\varepsilon}$ but we want to average only over the time scale 1 dynamics. This is achieved as follows: Consider, instead of (16) the following equation:

$$\dot{w} = \varepsilon f(w, t, \varepsilon t, \varepsilon). \quad (17)$$

Define $w_0 = \varepsilon t$ and substitute w_0 for εt in (17). Then, consider the system

$$\begin{aligned} \dot{w} &= \varepsilon f(w, t, w_0, \varepsilon), \\ \dot{w}_0 &= \varepsilon \end{aligned}$$

and apply averaging to it. The resulting averaged form of (17) is now

$$\dot{\bar{w}} = \varepsilon f_{av}(\bar{w}, \varepsilon t),$$

where

$$f_{av}(w, w_0) := \lim_{\tau \rightarrow \infty} \frac{1}{\tau} \int_t^{t+\tau} f(w, t', w_0, 0) dt'.$$

We now apply this to equation (15). Since the time average of $e^{i\omega t}$ is zero for $\omega \neq 0$ and 1 for $\omega = 0$, only terms with no time dependence will contribute to the averaged equation. Letting $\bar{x}$ be the averaged x , the averaged form of (15) is

$$i\dot{\bar{x}}_i = \varepsilon(V_{ii} u_0(\varepsilon t) \bar{x}_i + \sum_{j \neq i} V_{ij} u_{ij}(\varepsilon t) \bar{x}_j). \quad (18)$$

Taking $\varepsilon = \frac{1}{T}$ and rescaling time to $s = \varepsilon t = \frac{t}{T}$, (18) becomes

$$i \frac{d\bar{x}_i}{ds} = V_{ii} u_0(s) \bar{x}_i + \sum_{j \neq i} V_{ij} u_{ij}(s) \bar{x}_j, \quad (19)$$

or, in vector form,

$$i \frac{d\bar{x}}{ds} = \tilde{V}[u_0, u_{ij}] \bar{x},$$

where

$$\tilde{V}[u_0, u_{ij}] = \begin{pmatrix} V_{11}u_0 & V_{12}u_{12} & \cdots \\ V_{21}u_{21} & V_{22}u_0 & \cdots \\ \vdots & \vdots & \ddots \end{pmatrix} \bar{x} = \begin{pmatrix} V_{11}u_0 & V_{12}u_{12} & \cdots \\ V_{12}^*u_{12}^* & V_{22}u_0 & \cdots \\ \vdots & \vdots & \ddots \end{pmatrix} \bar{x}.$$

By construction, every solution to (19) with controls $u_0(s)$ and $u_{ij}(s)$ and initial state $\bar{x}(0) = \psi(0)$, provides a solution to (1) with $u(t)$ given by (14) and initial condition $\psi(0)$, correct up to $O(\varepsilon)$ terms for a time interval of size $\frac{1}{\varepsilon} = T$. It is shown in Appendix B that system (19) is controllable on account of the controllability assumption on the original system.

Since our goal is to relate optimal transfers of the original system to optimal transfers of the averaged one, we must find an objective for the averaged system that approximates $\|u\|_{L^2([0, T])}^2$. So, we compute $\|u\|_{L^2([0, T])}^2$ for $u(t)$ given by (14), with $\varepsilon = \frac{1}{T}$:

$$\begin{aligned} \int_0^T u^2(t) dt &= \frac{1}{T^2} \int_0^T \left(u_0\left(\frac{t}{T}\right) + \sum_{i \neq j} e^{i\omega_{ij}t} u_{ji}\left(\frac{t}{T}\right) \right)^2 dt \\ &= \frac{1}{T^2} \int_0^T \left\{ u_0^2\left(\frac{t}{T}\right) + 2 \sum_{i \neq j} e^{i\omega_{ij}t} u_{ji}\left(\frac{t}{T}\right) u_0\left(\frac{t}{T}\right) \right. \\ &\quad \left. + \sum_{i \neq j} \sum_{k \neq l} e^{i(\omega_{ij} + \omega_{kl})t} u_{ji}\left(\frac{t}{T}\right) u_{lk}\left(\frac{t}{T}\right) \right\} dt \end{aligned}$$

$$\begin{aligned}
&= \frac{1}{T} \int_0^1 \left\{ u_0^2(s) + 2 \sum_{i \neq j} e^{i\omega_{ij}Ts} u_{ji}(s) u_0(s) \right. \\
&\quad \left. + \sum_{i \neq j} \sum_{k \neq l} e^{i(\omega_{ij} + \omega_{kl})Ts} u_{ji}(s) u_{lk}(s) \right\} ds \\
&= \frac{1}{T} \int_0^1 \left[\sum_{i \neq j} u_{ij}(s) u_{ji}(s) + u_0^2(s) \right] ds + \frac{1}{T^2} B(T),
\end{aligned}$$

where $B(T)$ represents terms bounded in T . This last line is the result of separating the integrals into two kinds, these without exponentials, which are explicitly retained, and those with, which can easily be seen to scale like $\frac{1}{T}B(T)$ after a partial integration: Indeed, for any differentiable f ,

$$\begin{aligned}
\int_0^1 e^{i\omega Ts} f(s) ds &= \frac{1}{i\omega T} \int_0^1 (e^{i\omega Ts})' f(s) ds \\
&= \frac{1}{i\omega T} \{ e^{i\omega T} f(1) - f(0) - \int_0^1 e^{i\omega Ts} f'(s) ds \}.
\end{aligned}$$

So, we pose the following optimal control problem for the averaged system: Find controls $u_0(s)$, $u_{ij}(s)$, $s \in [0, 1]$, that minimize

$$\int_0^1 \left[\sum_{i \neq j} u_{ij}(s) u_{ji}(s) + u_0^2(s) \right] ds = \int_0^1 \left[\sum_{i \neq j} |u_{ij}(s)|^2 + u_0^2(s) \right] ds \quad (20)$$

and drive an initial state $\bar{x}(0) = \psi_0$ of system (19) to a target population distribution $\{|\bar{x}_i(1)|^2 = p_i, i = 1, \dots, N\}$. We will refer to this as optimal transfer problem (II).

The necessary conditions for optimality are derived from the Hamiltonian function

$$\begin{aligned}
H(\bar{x}_i, \bar{z}_i, u_{ij}) &= \frac{1}{2} u_0^2 + \frac{1}{2} \sum_{i \neq j} |u_{ij}|^2 - i \bar{z}^* \tilde{V}[u_0, u_{ij}] \bar{x} + i \bar{x}^* \tilde{V}[u_0, u_{ij}] \bar{z} \\
&= \frac{1}{2} u_0^2 + \sum_{i \neq j} \frac{1}{2} u_{ij} u_{ji} - i V_{ji} u_{ji} (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*) - i u_0 \sum_i V_{ii} (\bar{x}_i \bar{z}_i^* - \bar{z}_i \bar{x}_i^*)
\end{aligned}$$

and have the form

$$i \frac{d\bar{x}_i}{ds} = V_{ii} u_0 \bar{x}_i + \sum_{j \neq i} V_{ij} u_{ij} \bar{x}_j \quad (i \frac{d\bar{x}}{ds} = \tilde{V}[u_0, u_{ij}] \bar{x}), \quad (21)$$

$$i \frac{d\bar{z}_i}{ds} = V_{ii} u_0 \bar{z}_i + \sum_{j \neq i} V_{ij} u_{ij} \bar{z}_j \quad (i \frac{d\bar{z}}{ds} = \tilde{V}[u_0, u_{ij}] \bar{z}), \quad (22)$$

$$u_{ij} = i V_{ji} (x_i z_j^* - z_i x_j^*), \quad u_0 = i \sum_i V_{ii} (\bar{x}_i \bar{z}_i^* - \bar{z}_i \bar{x}_i^*). \quad (23)$$

We rewrite equations (21) and (22) using u_0 and u_{ij} from (23):

$$\frac{d\bar{x}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*) \bar{x}_j + \sum_k V_{kk} (\bar{x}_k \bar{z}_k^* - \bar{z}_k \bar{x}_k^*) V_{ii} \bar{x}_i, \quad (24)$$

$$\frac{d\bar{z}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*) \bar{z}_j + \sum_k V_{kk} (\bar{x}_k \bar{z}_k^* - \bar{z}_k \bar{x}_k^*) V_{ii} \bar{z}_i. \quad (25)$$

The corresponding boundary conditions are given by

$$\bar{x}(0) = \psi_0, \quad |\bar{x}_i(1)|^2 = p_i, \quad \text{Im}(\bar{x}_i^*(1) \bar{z}_i(1)) = 0. \quad (26)$$

We will refer to the two-point boundary value problem comprised of equations (24) - (26) as two-point boundary value problem (II). From (23), we see that all u_{ij} with $V_{ij} = 0$ are identically zero, as they should. We can also show that $u_0 = 0$ and simplify the right sides of equations (24) and (25): In a fashion similar to the construction of Λ in section 2, we define L by $L := \bar{x} \bar{z}^* - \bar{z} \bar{x}^*$. We also define another anti-Hermitian matrix $K = K(\bar{x}, \bar{z}) = K(L)$ by,

$$K_{ij} := |V_{ij}|^2 L_{ij} = |V_{ij}|^2 (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*), \quad i \neq j, \quad (27)$$

$$K_{ii} := V_{ii} \sum_k V_{kk} L_{kk} = V_{ii} \sum_k V_{kk} (\bar{x}_k \bar{z}_k^* - \bar{z}_k \bar{x}_k^*). \quad (28)$$

K is the analog of $-iH_0 + \text{tr}(V\Lambda)V$ in section (2) and is a linear function of L . With this definition, (24) and (25) read simply as

$$\frac{d\bar{x}}{ds} = K(L)\bar{x}, \quad (29)$$

$$\frac{d\bar{z}}{ds} = K(L)\bar{z}. \quad (30)$$

It is easy to see that L satisfies the differential equation

$$\frac{dL}{ds} = [K(L), L]. \quad (31)$$

The ii -th component of this equation reads

$$\begin{aligned} \frac{dL_{ii}}{ds} &= \sum_j K_{ij} L_{ji} - L_{ij} K_{ji} \\ &= K_{ii} L_{ii} + \sum_{j \neq i} K_{ij} L_{ji} - L_{ii} K_{ii} - \sum_{j \neq i} L_{ij} K_{ji} \\ &= \sum_{j \neq i} |V_{ij}|^2 (L_{ij} L_{ji} - L_{ij} L_{ji}) = 0, \end{aligned}$$

and so,

$$L_{ii}(s) = L_{ii}(1) = -2i \text{Im}(\bar{x}_i^*(1) \bar{z}_i(1)) = 0. \quad (32)$$

This shows that $K_{ii}(s) = L_{ii}(s) = 0$ and $u_0(s) = 0$ and so, equations (24) and (25) simplify to

$$\frac{d\bar{x}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*) \bar{x}_j, \quad (33)$$

$$\frac{d\bar{z}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*) \bar{z}_j. \quad (34)$$

We will refer to this set of equations (along with (26)) as two-point boundary value problem (II) as well.

4 Main Results

In this section, we make the connection between solutions of the two-point boundary value problems (II) and (I) in the large T limit.

Theorem 1: Let $(\bar{x}(s), \bar{z}(s))$ be a solution of two-point boundary value problem (II) over $[0, 1]$. Define $\psi(t)$, $\lambda(t)$ and $u(t)$, $t \in [0, T]$, by

$$\psi(t) = e^{-iH_0 t} \bar{x}\left(\frac{t}{T}\right), \quad (35)$$

$$\lambda(t) = \frac{1}{T} e^{-iH_0 t} \bar{z}\left(\frac{t}{T}\right), \quad (36)$$

$$u(t) = \frac{i}{T} \text{tr}(e^{iH_0 t} V e^{-iH_0 t} L\left(\frac{t}{T}\right)) = \frac{i}{T} \sum_{kl} V_{kl} e^{i\omega_{kl} t} L_{lk}\left(\frac{t}{T}\right). \quad (37)$$

Then, for large enough T , $\psi(t)$ satisfies the necessary conditions of optimality (4) - (9), up to terms of order $O(\frac{1}{T})$ and $\lambda(t)$ and $u(t)$ up to terms of order $O(\frac{1}{T^2})$.

Thus, solutions of the two-point boundary value problem (II) provide *approximate* solutions to the two-point boundary value problem (I) for large transfer times T . A natural question to ask then is, whether these approximate solutions to two-point boundary value problem (I) are in fact *approximations to solutions* of (I), in the large T limit. This is answered positively by the following theorem:

Theorem 2: Let ψ_0 and $\{p_i\}_{i=1, \dots, N}$ be an initial state and a target population of system (1), respectively, and let $(\bar{x}(s), \bar{z}(s))$ be a solution of two-point boundary value problem (II) over $[0, 1]$. Then, for almost all pairs $(\psi_0, \{p_i\})$, a solution of two-point boundary value problem (I) exists, for large enough T , of the form

$$\psi(t) = e^{-iH_0 t} \bar{x}\left(\frac{t}{T}\right) + O\left(\frac{1}{T}\right), \quad (38)$$

$$\lambda(t) = \frac{1}{T} e^{-iH_0 t} \bar{z}\left(\frac{t}{T}\right) + O\left(\frac{1}{T^2}\right), \quad (39)$$

The corresponding control has the form

$$\begin{aligned} u(t) &= \frac{i}{T} \text{tr}(e^{iH_0 t} V e^{-iH_0 t} L(\frac{t}{T})) + O(\frac{1}{T^2}) \\ &= \frac{i}{T} \sum_{kl} V_{kl} e^{i\omega_{kl} t} L_{lk}(\frac{t}{T}) + O(\frac{1}{T^2}). \end{aligned} \quad (40)$$

The set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations for which a solution of two-point boundary value problem (II) provides a solution of (I) according to (38) and (39) is open and full measure in the corresponding product manifold.

According to this theorem, solutions to the two-point boundary value problem (II) approximate solutions to (I), for large transfer times, in the sense of equations (38) - (40), for almost every population transfer. In other words, all the local minima of optimal transfer problem (II) approximate local minima for the optimal transfer problem (I) according to (38) - (40). The question arises naturally: Are *all* local minima of optimal transfer problem (I), for large T , approximated in the sense of equations (38) - (40) by local minima of (II)? The answer to this question is essentially yes (see comment after theorem 3). We state the following theorem:

Theorem 3: Let ψ_0 and $\{p_i\}_{i=1,\dots,N}$ be an initial state and a target population of system (1), respectively. Then, for almost all pairs $(\psi_0, \{p_i\})$ and for large enough T , the globally optimal solution to the optimal transfer problem (I) is approximated by the globally optimal solution of (II) according to theorem 2. As before, the set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations for which this happens is open and full measure in the corresponding product manifold.

In fact, we prove that, for large enough T , a number of the lowest energy optima of (I) that depends (in an unknown way) on T , are approximated by the corresponding lowest energy optima of (II) according to theorem 2. We think though, that theorem 3 is enough to demonstrate the spirit of our approach.

Theorem 3 precisely states the main results of our work that were delineated in the introduction: We obtain useful, physically plausible properties of the optimal control and state trajectory and at the same time, we reduce the solution of the original optimal control problem to a much easier problem: Indeed, the evolution equations (33) and (34) of two-point boundary value problem (II) do not contain the free dynamics of the system and thus their solution (which describes the “mean” evolution of the state) is much easier, see section 6.

We end this section with two remarks:

1. Theorems 2 and 3 are proven for an open, full measure set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations. Unfortunately, the very important case of the initial state ψ_0 being an eigenstate (or, in general, having some populations equal to 0) is excluded. The reason is that in this case, two-point boundary value problem (II) has non-isolated solutions. Although this property is necessary for our proof of these results,

we believe that they can be extended to (at least some) transfers with non-isolated solutions. Nevertheless, theorem (I) which contains all the essential *applicable* aspects of this work still holds.

2. An interesting implication of the theorem above is that, for large T , the locally optimal values of the objective (“energy”) scale like $\frac{1}{T}$. This demonstrates that the quadratic objective we use, cannot correspond to a physical notion of energy. It could be that an objective like

$$\int_0^T |u(t)| dt,$$

would be more appropriate for that purpose in the context of (1).

5 Proof of Main Results

Proof of Theorem 1

To begin, we define a new costate variable by $\tilde{\lambda} := T\lambda$ and rewrite (7) and (8) in terms of $\tilde{\lambda}$:

$$i\dot{\psi} = H_0\psi + \frac{i}{T}(\tilde{\lambda}^*V\psi - \psi^*V\tilde{\lambda})V\psi, \quad (41)$$

$$i\dot{\tilde{\lambda}} = H_0\tilde{\lambda} + \frac{i}{T}(\tilde{\lambda}^*V\psi - \psi^*V\tilde{\lambda})V\tilde{\lambda}. \quad (42)$$

Note that the form of the boundary conditions remains unchanged, as well:

$$\psi(0) = \psi_0, \quad |\psi_i(T)|^2 = p_i, \quad \text{Im}(\psi_i^*(T)\tilde{\lambda}_i(T)) = 0. \quad (43)$$

We must show that $e^{-iH_0t}\tilde{x}(\frac{t}{T})$ and $e^{-iH_0t}\tilde{z}(\frac{t}{T})$ satisfy (41) - (43) up to terms of order $O(\frac{1}{T})$. To this purpose, we perform one more change of variables in (41) - (43):

$$y = e^{iH_0t}\psi, \quad l = e^{iH_0t}\tilde{\lambda}.$$

In terms of the new state and costate, the necessary conditions of optimality take the form

$$i\dot{y} = \frac{i}{T}(l^*F(t)y - y^*F(t)l)F(t)y, \quad (44)$$

$$i\dot{l} = \frac{i}{T}(l^*F(t)y - y^*F(t)l)F(t)l, \quad (45)$$

where, as before, $F(t) = e^{iH_0t}V e^{-iH_0t}$, along with

$$y(0) = \psi_0, \quad |y_i(T)|^2 = p_i, \quad \text{Im}(y_i^*(T)l_i(T)) = 0. \quad (46)$$

The boundary conditions retain their form because $|y_i(T)|^2 = |\psi_i(T)|^2$ and, $l_i(T)$ and $y_i(T)$ are rotated by the same amount, e^{-iE_iT} , with respect to $\psi_i(T)$

and $\tilde{\lambda}_i(T)$. We will refer to equations (44) - (46) as two-point boundary value problem (I'). The equivalence of problems (I) and (I') is evident.

Now, we have to show that $\bar{x}(\frac{t}{T})$ and $\bar{z}(\frac{t}{T})$ satisfy (44) - (46) up to terms of order $O(\frac{1}{T})$. To do this, we average equations (44) and (45). To make the procedure more transparent, we rewrite equations (44) and (45) in component form:

$$\begin{aligned}\dot{y}_i &= \frac{1}{T} \left(\sum_{km} V_{km} e^{i\omega_{km}t} (l_k^* y_m - y_k^* l_m) \right) \sum_j V_{ij} e^{i\omega_{ij}t} y_j \\ \dot{l}_i &= \frac{1}{T} \left(\sum_{km} V_{km} e^{i\omega_{km}t} (l_k^* y_m - y_k^* l_m) \right) \sum_j V_{ij} e^{i\omega_{ij}t} l_j\end{aligned}$$

One can see (based on our controllability assumption) that we get non-zero contributions from two groups of terms: Terms with $\omega_{km} \neq 0$ and $\omega_{ij} \neq 0$ such that $m = i$ and $k = j$, and terms with $\omega_{km} = \omega_{ij} = 0$, i.e. $k = m$ and $i = j$. Letting $\bar{y}$ and $\bar{l}$ be the averaged y and l , the averaged state and co-state equations are:

$$\dot{\bar{y}}_i = \frac{1}{T} \left\{ \sum_{j \neq i} |V_{ij}|^2 (\bar{y}_i \bar{l}_j^* - \bar{l}_i \bar{y}_j^*) \bar{y}_j + \sum_k V_{kk} (\bar{y}_k \bar{l}_k^* - \bar{l}_k \bar{y}_k^*) V_{ii} \bar{y}_i \right\}, \quad (47)$$

$$\dot{\bar{l}}_i = \frac{1}{T} \left\{ \sum_{j \neq i} |V_{ij}|^2 (\bar{y}_i \bar{l}_j^* - \bar{l}_i \bar{y}_j^*) \bar{l}_j + \sum_k V_{kk} (\bar{y}_k \bar{l}_k^* - \bar{l}_k \bar{y}_k^*) V_{ii} \bar{l}_i \right\}. \quad (48)$$

To finish the proof, we rescale time in equations (47) and (48) to $s = \varepsilon t = \frac{t}{T}$. Letting $\tilde{y}(s) := \bar{y}(t)$ and $\tilde{l}(s) := \bar{l}(t)$, these equations read now:

$$\frac{d\tilde{y}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\tilde{y}_i \tilde{l}_j^* - \tilde{l}_i \tilde{y}_j^*) \tilde{y}_j + \sum_k V_{kk} (\tilde{y}_k \tilde{l}_k^* - \tilde{l}_k \tilde{y}_k^*) V_{ii} \tilde{y}_i, \quad (49)$$

$$\frac{d\tilde{l}_i}{ds} = \sum_{j \neq i} |V_{ij}|^2 (\tilde{y}_i \tilde{l}_j^* - \tilde{l}_i \tilde{y}_j^*) \tilde{l}_j + \sum_k V_{kk} (\tilde{y}_k \tilde{l}_k^* - \tilde{l}_k \tilde{y}_k^*) V_{ii} \tilde{l}_i. \quad (50)$$

These equations are the same as (24) and (25) (with the substitution $\tilde{y} \rightarrow \bar{x}$ and $\tilde{l} \rightarrow \bar{z}$). Then, from the sequence of variable changes and the averaging theorem, the conclusion of the theorem follows. ■

Proof of Theorem 2

To prove Theorem 2 we need the following lemma:

Lemma: Let ψ_0 and $\{p_i\}_{i=1,\dots,N}$ be an initial state and a target population of system (1), respectively, and let $(\bar{x}(s), \bar{z}(s))$ be a solution of two-point boundary value problem (II) over $[0, 1]$. The set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations for which all solutions of two-point boundary value problem

(II) are *isolated* is open and full measure in the corresponding product manifold.

Proof of Lemma: We begin by introducing new coordinates for the state and costate of the optimal transfer problem (II) by

$$\bar{x}_i := I_i e^{i\phi_i}, \quad \bar{z}_i := J_i e^{i\theta_i}, \quad (51)$$

where $\phi_i := \arg \bar{x}_i \bmod \pi$ and $I_i := |\bar{x}_i|$ for $\text{Im} \bar{x}_i \geq 0$ and $I_i := -|\bar{x}_i|$ for $\text{Im} \bar{x}_i < 0$, and similarly for the θ_i 's and J_i 's. Then, $I_i, J_i \in \mathbb{R}$ and $\phi_i, \theta_i \in [0, \pi)$, $\forall i = 1, \dots, N$. With this definition, the phases ϕ_i and θ_i have discontinuities whenever the signs of the imaginary parts of $\bar{x}_i$ and $\bar{z}_i$ change. We shall see that this will not be a problem for us because ϕ_i and θ_i will turn out to be constant in time. On the other hand, the introduction of these coordinates will prove to be beneficial in the following.

In the new coordinates, (33) and (34), take the form

$$i\dot{I}_i - I_i\dot{\phi}_i = +iI_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j e^{i(\phi_j - \theta_j)} - iJ_i e^{i(\theta_i - \phi_i)} \sum_{j \neq i} |V_{ij}|^2 I_j^2, \quad (52)$$

$$i\dot{J}_i - J_i\dot{\theta}_i = -iJ_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j e^{i(\theta_j - \phi_j)} + iI_i e^{i(\phi_i - \theta_i)} \sum_{j \neq i} |V_{ij}|^2 J_j^2, \quad (53)$$

while the boundary conditions at the end become

$$I_i^2(1) = p_i, \quad \theta_i(1) - \phi_i(1) = 0. \quad (54)$$

Multiply (52) by J_i , (53) by $-I_i$, add them and take the real part. The resulting equation reads:

$$I_i J_i (\phi_i - \theta_i)' = \sin(\phi_i - \theta_i) \{ I_i^2 \sum_{j \neq i} |V_{ij}|^2 J_j^2 - J_i^2 \sum_{j \neq i} |V_{ij}|^2 I_j^2 \}. \quad (55)$$

Except for the degenerate cases ($I_i(s) = 0, J_i(s) = \text{const.}$) and ($J_i(s) = 0, I_i(s) = \text{const.}$) $\forall s \in [0, 1]$, which will be excluded, we see that, given the transversality conditions at $s = 1$, this equation implies that $\theta_i(s) = \phi_i(s)$, $\forall s \in [0, 1]$. Using this fact, we see that the right sides of equations (52) and (53) are purely imaginary. This leads to the simplified equations

$$\begin{aligned} \dot{I}_i &= +I_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j - J_i \sum_{j \neq i} |V_{ij}|^2 I_j^2, \\ \dot{J}_i &= -J_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j + I_i \sum_{j \neq i} |V_{ij}|^2 J_j^2, \\ \dot{\phi}_i(s) &= 0, \quad \dot{\theta}_i(s) = 0. \end{aligned}$$

We see that the two-point boundary value problem (II) separates nicely into two parts: A trivial problem for the arguments of state and costate components

$$\dot{\phi}_i(s) = 0, \quad \dot{\theta}_i(s) = 0, \quad (56)$$

$$\phi_i(0) = \phi_{i0}, \quad \theta_i(1) - \phi_i(1) = 0, \quad (57)$$

which has a unique solution as long as $\psi_{0i} \neq 0$, $\forall i = 1, \dots, N$ (so that all $\phi_i(0)$ are unambiguously defined) and a two-point boundary value problem for the (signed) magnitudes of state and costate components

$$\dot{I}_i = +I_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j - J_i \sum_{j \neq i} |V_{ij}|^2 I_j^2, \quad (58)$$

$$\dot{J}_i = -J_i \sum_{j \neq i} |V_{ij}|^2 I_j J_j + I_i \sum_{j \neq i} |V_{ij}|^2 J_j^2, \quad (59)$$

$$I_i(0) = I_{i0}, \quad I_i^2(1) = p_i. \quad (60)$$

We will refer to (58) - (60) as the real form of problem (II). These two-point boundary value problems can be seen to be necessary conditions for optimal population transfers of the following *real* control system on S^{N-1} :

$$\frac{dI}{ds} = \begin{pmatrix} 0 & |V_{12}|v_{12} & \cdots \\ -|V_{21}|v_{21} & 0 & \cdots \\ \vdots & \vdots & \ddots \end{pmatrix} I. \quad (61)$$

Here the v_{ij} are real controls and (61) is controllable on S^{N-1} because of the controllability assumption on the original system, see Appendix B. This separation of the two-point boundary value problem (II) into a trivial problem for the evolution of the arguments of state and costate components and real two-point boundary value problem (II) was inspired by the result of [20], see section 4 of that reference.

We are now ready to prove the lemma. From the discussion so far, it should be obvious that we need $\psi_{i0} \neq 0$ and $|\psi_{0i}|^2 \neq p_i, \forall i = 1, \dots, N$ so that the (constant) phases of the state components are uniquely defined and certain pathological cases mentioned are excluded. The set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations for which this is the case is open and full measure in the corresponding product manifold.

We define a terminal condition function $\mathcal{G}$ of the initial costate vector $J(0)$ of real problem (II) by

$$\mathcal{G}(J(0)) := (I_2(1)^2, \dots, I_N(1)^2)^T. \quad (62)$$

$\mathcal{G}$ is really a function of only $N - 1$ components of $J(0)$ because one of them is fixed by the condition $0 = \bar{x}^*(0)\bar{z}(0) = I^T(0)J(0)$ (let us decide to fix $J_1(0)$). Similarly, once $(I_2(1)^2, \dots, I_N(1)^2)$ are fixed, so is $I_1(1)^2$, and that is why we need only $N - 1$ terminal conditions. In the following, when talking about initial costate vectors, we will identify vectors in $\mathbb{R}^{N-1}$ with vectors in $\mathbb{R}^N$ perpendicular to I_0 . $\mathcal{G}$ has two important properties: First, it is a smooth function of its argument. Indeed, the right sides of (58) and (59) are C^2 functions of I and J so, [22] their solutions depend smoothly on $I(0)$ and $J(0)$. Thus, when $I(0)$ is fixed, the terminal conditions depend smoothly on $J(0)$. Second, because of controllability of system (61), $\mathcal{G}$ is onto. Since $\mathcal{G}$ is a mapping

between manifolds of the same dimension, it is a diffeomorphism from (open) neighborhoods of $\mathbb{R}^{N-1}$ to neighborhoods of the $N-1$ dimensional simplex. Sard's theorem implies that the set of critical values of $\mathcal{G}$ in the $N-1$ dimensional simplex (i.e. the set of points around which $\mathcal{G}$ is not a diffeomorphism) is of measure zero.

Any initial costate vector $J(0)$ such that $\mathcal{G}(J(0)) = (p_1, \dots, p_N)^T$ provides a solution to real problem (II). Because of the two properties of $\mathcal{G}$, the set of p_i 's for which *all* $J(0)$ that satisfy $\mathcal{G}(J(0)) = (p_1, \dots, p_N)^T$ satisfy also $\mathcal{N}(D\mathcal{G}(J(0))) = \emptyset$, is an open set of full measure in S^{N-1} . For a pair of initial state and final populations which satisfy this, the set of $J(0)$'s must be discrete and without limit points, otherwise, $\mathcal{N}(D\mathcal{G}(J(0))) \neq \emptyset$ for at least one of the $J(0)$'s. This means that, given an initial state with all populations non-zero, the set of populations that can be achieved by *isolated* locally optimal transfers of the real problem (II) is open and full measure. So, the set of pairs $(\psi_0, \{p_i\})$ of initial states and target populations for which all solutions of two-point boundary value problem (II) are *isolated* is open and full measure in the corresponding product manifold. ■

Proof of Theorem 2: We are going to define terminal condition functions for two-point boundary value problems (II) and (I') in a way similar to that in the proof of the lemma. First, for (II) we define $\mathcal{F} : \mathbb{R}^{2N-2} \longrightarrow \mathbb{R}^{2N-2}$ by

$$\mathcal{F}(\bar{z}(0)) := (|\bar{x}_2^2(1)|, \dots, |\bar{x}_N^2(1)|, \text{Im}(\bar{x}_2^*(1) \bar{z}_2(1)), \dots, \text{Im}(\bar{x}_N^*(1) \bar{z}_N(1)))^T \quad (63)$$

(Recall that one complex component of $\bar{z}(0)$ is fixed by $\bar{x}^*(0)\bar{z}(0) = 0$. Here, we again identify initial costate vectors in $\mathbb{C}^N$ perpendicular to ψ_0 with vectors in $\mathbb{C}^{N-1}$ and also identify $\mathbb{C}^{N-1}$ with $\mathbb{R}^{2N-2}$). $\mathcal{F}$ is a smooth function of its argument. Also, any initial costate vector $\bar{z}(0)$ such that $\mathcal{F}(\bar{z}(0)) = (p_2, \dots, p_N, 0, \dots, 0)^T$ provides a solution to problem (II).

The corresponding terminal condition function $\mathcal{F}_1$ for problem (I'), is defined exactly the same way:

$$\mathcal{F}_1(l(0); T) := (|y_2(T)|^2, \dots, |y_N(T)|^2, \text{Im}(y_2^*(T) l_2(T)), \dots, \text{Im}(y_N^*(T) l_N(T)))^T \quad (64)$$

The second argument of $\mathcal{F}_1$ is just a reminder of the transfer time. $\mathcal{F}_1$ is also a smooth function of its argument. Again, any initial costate vector $y(0)$ such that $\mathcal{F}_1(y(0)) = (p_2, \dots, p_N, 0, \dots, 0)^T$ provides a solution to problem (I'). From the proof of theorem (I), we know that

$$\mathcal{F}_1(v; T) = \mathcal{F}(v) + O\left(\frac{1}{T}\right). \quad (65)$$

From this we also have that

$$D\mathcal{F}_1(v; T) = D\mathcal{F}(v) + O\left(\frac{1}{T}\right).$$

Although $\mathcal{F}_1$ is not formally defined for $T = \infty$ from (64), we can define it from (65) as $\mathcal{F}_1(v; 0) := \mathcal{F}(v)$. With this definition, $\mathcal{F}_1$ is continuous in $\frac{1}{T}$

at $\frac{1}{T} = 0$, with continuous first derivatives in v and $\frac{1}{T}$ there. In particular, $D\mathcal{F}_1(v; \infty) = D\mathcal{F}(v)$.

Consider now an initial costate vector v that solves problem (II), i.e.

$$\mathcal{F}(v) = (p_2, \dots, p_N, 0, \dots, 0)^T$$

We have seen that the set of pairs $(\psi_0, \{p_i\})$ such that *all* v 's that satisfy this are isolated ($D\mathcal{F}(v)$ full rank), is an open set of full measure in the product space. For such a transfer and for large enough T , the implicit function theorem guarantees the existence of a δv such that $\mathcal{F}_1(v + \delta v; T) = (p_2, \dots, p_N, 0, \dots, 0)^T$. Then, $v + \delta v$ provides a solution for problem (I') and $\frac{v + \delta v}{T}$ is a solution for problem (I). Taking T large enough so that $|\delta v| = O(\frac{1}{T})$, the averaging theorem guarantees that this solution $(\psi(t), \lambda(t))$ to two-point boundary value problem (I) is such that

$$\begin{aligned}\psi(t) &= e^{-iH_0 t} \bar{x}\left(\frac{t}{T}\right) + O\left(\frac{1}{T}\right), \\ \lambda(t) &= \frac{1}{T} e^{-iH_0 t} \bar{z}\left(\frac{t}{T}\right) + O\left(\frac{1}{T^2}\right),\end{aligned}$$

where $(\bar{x}(s), \bar{z}(s))$ is the solution to problem (II) we started with. ■

Proof of Theorem 3

We only consider transfers such that problem (II) has isolated solutions. Any initial costate v that satisfies $\mathcal{F}(v) = (p_2, \dots, p_N, 0, \dots, 0)^T$ provides a solution to problem (II) and $D\mathcal{F}(v)$ is full rank. Inside a ball of radius $M > 0$ there can be only a *finite* number of these initial costates v because any discrete set with no limit points inside a compact set must be finite.

From equation (65) we may conclude that for a given transfer, we can take T large enough to bound the difference of $\mathcal{F}$ and $\mathcal{F}_1$ over an open ball around the origin by any $\delta > 0$:

$$\forall M > 0, \forall \delta > 0, \exists T > 0 \text{ such that } |\mathcal{F}_1(v; T) - \mathcal{F}(v)| < \delta, \forall |v| < M.$$

Thus, the only solutions of $\mathcal{F}_1(\tilde{v}; T) = (p_2, \dots, p_N, 0, \dots, 0)^T$ inside the ball of radius M come from perturbing solutions of $\mathcal{F}(v) = (p_2, \dots, p_N, 0, \dots, 0)^T$ by quantities of order $O(\frac{1}{T})$, for T large enough. In particular, they also form a finite set and $D\mathcal{F}_1(\tilde{v}; T)$ is full rank for each such $\tilde{v}$. We arrive at exactly the same conclusion if, instead of a ball, we define a neighborhood of the origin by an ellipsoid.

We introduce now the following quadratic form in $v \in \{w \in \mathbb{C}^N \text{ s.t. } \psi_0^* w = 0\} \simeq \mathbb{C}^{N-1} \simeq \mathbb{R}^{2N-2}$:

$$E(v) = \sum_{i \neq j}^N |V_{ij}|^2 |\psi_{0i} v_j^* - v_i \psi_{0j}^*|^2.$$

E is non-negative and, furthermore, due to the connectivity of the graph of V (part of the controllability assumption) can be shown to be positive definite, see Appendix C. Then, the sub-level sets of E define (open) ellipsoids in $\mathbb{R}^{2N-2}$. The significance of our choice for $E(v)$ lies in the following:

$$H(\bar{x}, \bar{z}) = \sum_{i \neq j} |V_{ji}|^2 |\bar{x}_i \bar{z}_j^* - \bar{z}_i \bar{x}_j^*|^2$$

is the Hamiltonian function from which the optimal state and costate equations (33) and (34) are derived. Thus, H is a constant of motion along the optimal solutions. Note, also, that $H(\bar{x}, \bar{z}) = \sum_{i \neq j} |u_{ij}|^2$. Since E is just H evaluated at $t = 0$, we conclude that E is equal to the cost of a trajectory of system (II) (equations (33) and (34)) with initial conditions (ψ_0, v) :

$$\int_0^1 \sum_{i \neq j} |u_{ij}(s)|^2 ds = H(0) = \sum_{i \neq j}^N |V_{ij}|^2 |\psi_{0i} v_j^* - v_i \psi_{0j}^*|^2.$$

With a calculation similar to that of section 3, one can show that the locally optimal costs for problems (II) and (I/I') coming from the solutions v and $\tilde{v} = v + O(\frac{1}{T})$, respectively are related as follows:

$$\begin{aligned} \int_0^T u^2(t) dt &= \frac{1}{T} \left(\int_0^1 \sum_{i \neq j} |u_{ij}(s)|^2 ds + O\left(\frac{1}{T}\right) \right) \\ &= \frac{1}{T} \left(\sum_{i \neq j}^N |V_{ij}|^2 |\psi_{0i} v_j^* - v_i \psi_{0j}^*|^2 + O\left(\frac{1}{T}\right) \right). \end{aligned}$$

Let us fix a value $E_0 > 0$ such that the initial costate v_0 that achieves the desired transfer with the *minimum* energy for problem (II) satisfies

$$\sum_{i \neq j}^N |V_{ij}|^2 |\psi_{0i} v_j^* - v_i \psi_{0j}^*|^2 < E_0.$$

Then, for large enough T , $\tilde{v}_0 = v_0 + O(\frac{1}{T})$ is the initial costate that achieves the desired transfer with the *minimum* energy for problem (I'). This proves the assertion of the theorem. In fact, we proved a little bit more: Not only the global optimum, but also all local optima of problem (I') with values of energy less than $\frac{E_0}{T}$, come from local optima of problem (II) according to the theorem 2, for T large enough (Note that the solutions $\tilde{v}$ of problem (I/I') *outside* the ellipsoid $E(\tilde{v}) < E_0$ have higher costs than those inside the ellipsoid).■

6 Examples

We consider three examples, each involving a different quantum system: A general two-state system with one control, a general three-state system with

one control and the Morse oscillator model for the vibrational dynamics of the ground electronic state of the OH bond. We restrict our attention to the 22-dimensional space of bound states for that model and seek to control populations again with one control field. In all of the examples, we consider transfers from one eigenstate of the system, to another. Although in the proof of theorems 2 and 3 we had to exclude such transfers (because in that case two-point boundary value problem (II) has continua of solutions parameterized by angles, see (56) and (57), and we need isolated solutions to prove the theorems), we believe these theorems to hold for such transfers as well. Perhaps this can be established using different techniques from ours. In any case, theorem 1 still holds and so, every solution of two-point boundary value problem (II) will furnish an approximate solution to (I).

A two-state system

Consider the two-level system $i\dot{\psi} = (H_0 + Vu)\psi$, $\psi \in \mathbb{C}^2$, with

$$H_0 = \begin{pmatrix} E_1 & 0 \\ 0 & E_2 \end{pmatrix}, \quad \text{and} \quad V = \begin{pmatrix} V_{11} & V_{12} \\ V_{12}^* & V_{22} \end{pmatrix}.$$

By rescaling u , we make $|V_{12}| = 1$. We are interested in the “population inversion” transfer

$$\psi_0 = \begin{pmatrix} 1 \\ 0 \end{pmatrix} \longrightarrow \psi_d = \begin{pmatrix} 0 \\ 1 \end{pmatrix}.$$

In this example, the averaged optimal transfer problem (II) can be solved analytically. To begin, we introduce the anti-Hermitian matrices L and $K(L)$ of section (3):

$$L = \begin{pmatrix} 0 & L_{12} \\ -L_{12}^* & 0 \end{pmatrix} \quad \text{and} \quad K(L) = L.$$

Then, (31) implies that $L_{12}(s)$, $s \in [0, 1]$, is constant. Equation (29) reads

$$\frac{d\bar{x}}{ds} = \begin{pmatrix} 0 & L_{12} \\ -L_{12}^* & 0 \end{pmatrix} \bar{x}.$$

Its solution with initial condition $\begin{pmatrix} 1 \\ 0 \end{pmatrix}$, is given by

$$\bar{x}(s) = \begin{pmatrix} \cos(|L_{12}|s) \\ -i\frac{L_{12}}{|L_{12}|} \sin(|L_{12}|s) \end{pmatrix}.$$

To achieve $\bar{x}(1) = \begin{pmatrix} 0 \\ e^{i*} \end{pmatrix}$, we must have $|L_{12}| = (n + \frac{1}{2})\pi$, with $n \in \mathbb{N}$. The value of the cost (20) is $\frac{\pi^2}{2}(2n+1)^2$. Thus, $n = 0$ corresponds to the global minimum of optimal transfer problem (II). The approximate optimal control for problem (I) has the form (40)

$$u(t) = -\frac{\pi}{T} \sin(\omega_{21}t + \varphi),$$

where $\varphi \in [0, 2\pi)$ comes from the phases of L_{12} and V_{12} .

Figure (1) shows the evolution of populations in a two-state system with $\omega_{21} = 1$ under the approximate optimal control, for $T = 10\pi$ and $T = 6\pi$. Note that even for $T = 6\pi$, the averaged equations are still a good approximation to the full dynamics.




Figure 1: Averaged (dashed line) and exact (full line) populations of the two-state system under the approximate optimal control, for $T = 10\pi$ and $T = 6\pi$.

A three-state system

Let us now consider the general three-state system with one control and

$$H_0 = \begin{pmatrix} E_1 & 0 & 0 \\ 0 & E_2 & 0 \\ 0 & 0 & E_3 \end{pmatrix} \text{ and } V = \begin{pmatrix} V_{11} & V_{12} & V_{13} \\ V_{12}^* & V_{22} & V_{23} \\ V_{13}^* & V_{23}^* & V_{33} \end{pmatrix}.$$

We assume that $\omega_{12} = E_1 - E_2$, $\omega_{13} = E_1 - E_3$ and $\omega_{23} = E_2 - E_3$ are all different from each other and from zero. Their exact values are unimportant for the averaged optimal transfer problem as are the values of V_{11} , V_{22} and V_{33} . By rescaling the control, we can take $|V_{12}| = 1$ (we assume $|V_{12}| \neq 0$). Define $p := |V_{23}|^2$ and $r := |V_{13}|^2$. We assume that $1 > p > r \geq 0$, with other cases treated similarly. We are interested in the transfer

$$\psi_0 = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix} \longrightarrow \psi_d = \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix},$$

particularly in the way the “two-photon” transition

$$\begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix} \longrightarrow \begin{pmatrix} 0 \\ 1 \\ 0 \end{pmatrix} \longrightarrow \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix},$$

assists the “direct” (“one-photon”) transition

$$\begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix} \longrightarrow \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix}.$$

In this example, we are able to calculate the form of the (locally) optimal controls for the averaged problem analytically up to a constant, which has to be computed by solving the state evolution equations numerically and imposing the terminal conditions on the state. For a special case ($p = 1$), we can obtain everything analytically. We begin again with equation (31), $\frac{dL}{ds} = [K(L), L]$. The diagonal elements of L are zero and L is anti-Hermitian, so it has only 3 independent (complex) entries, L_{12} , L_{23} and L_{13} . They satisfy the following equations:

$$\begin{aligned} \frac{dL_{12}}{ds} &= (p - r)L_{13}L_{23}^*, \\ \frac{dL_{23}}{ds} &= (r - 1)L_{12}^*L_{13}, \\ \frac{dL_{13}}{ds} &= (1 - p)L_{12}L_{23}. \end{aligned}$$

Because $\bar{x}_2(0) = \bar{x}_3(0) = 0$, we have that $L_{32}(0) = 0$. The general solution of the above equations with $L_{32}(0) = 0$ is

$$\begin{aligned} L_{12}(s) &= e^{i\phi_{12}} A \operatorname{cn}(ws), \\ L_{23}(s) &= -e^{i\phi_{23}} B \operatorname{sn}(ws), \\ L_{13}(s) &= e^{i(\phi_{12} + \phi_{23})} C \operatorname{dn}(ws), \end{aligned}$$

where $w > 0$. cn , sn and dn are Jacobi elliptic functions and

$$\begin{pmatrix} A \\ B \\ C \end{pmatrix} = \frac{1}{\sqrt{(1-p)(1-r)(p-r)}} \begin{pmatrix} kw\sqrt{p-r} \\ kw\sqrt{1-r} \\ w\sqrt{1-p} \end{pmatrix}.$$

$0 \leq k \leq 1$ is the modulus of the elliptic functions. Now, from $\bar{x}_1(1) = \bar{x}_2(1) = 0$, we have that $L_{12}(1) = 0$. This allows us to determine w as $w = (2n + 1)K(k)$, $n \in \mathbb{N}$, where

$$K(k) := \int_0^{\frac{\pi}{2}} \frac{d\theta}{\sqrt{1 - k^2 \sin^2 \theta}},$$

the complete elliptic integral of the first kind, is the quarter-period of the functions cn and sn . The only undetermined parameter is k . It can be solved for numerically by solving the two-point boundary value problem given by (29),

$$\frac{d\bar{x}}{ds} = \begin{pmatrix} 0 & e^{i\phi_{12}} A \text{cn}(ws) & e^{i(\phi_{12}+\phi_{23})} rC \text{dn}(ws) \\ -e^{-i\phi_{12}} A \text{cn}(ws) & 0 & -e^{i\phi_{23}} pB \text{sn}(ws) \\ -e^{-i(\phi_{12}+\phi_{23})} rC \text{dn}(ws) & e^{-i\phi_{23}} pB \text{sn}(ws) & 0 \end{pmatrix} \bar{x},$$

and the boundary conditions

$$\bar{x}(0) = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix}, \quad \bar{x}(1) = \begin{pmatrix} 0 \\ 0 \\ e^{i*} \end{pmatrix}.$$

It is straightforward to see that the phases ϕ_{12} , ϕ_{23} and $\phi_{12}+\phi_{23}$ can be absorbed in the phases of the components of $\bar{x}$, so k is independent of them and depends only on p and r . Intuitively, one expects a discrete set of solutions for k . The cost of a local minimizer is given by

$$\begin{aligned} J &= 2 \int_0^1 [|u_{12}(s)|^2 + |u_{23}(s)|^2 + |u_{13}(s)|^2] ds \\ &= 2 \int_0^1 (A^2 \text{cn}^2(ws) + rC^2 \text{dn}^2(cs) + pB^2 \text{dn}^2(cs)) ds \\ &= \frac{2(2n+1)^2 K^2(k)}{(1-p)(1-r)(p-r)} [(p-r)k^2 + r(1-p)]. \end{aligned}$$

The expression for the approximate locally optimal controls of optimal transfer problem (I) is

$$\begin{aligned} u(t) = \frac{2}{T} \Big\{ & -A \text{cn}(w \frac{t}{T}) \sin(\omega_{21}t - \alpha_{12} + \phi_{12}) + \\ & \sqrt{p} B \text{sn}(w \frac{t}{T}) \sin(\omega_{32}t - \alpha_{23} + \phi_{23}) - \\ & \sqrt{r} C \text{dn}(w \frac{t}{T}) \sin(\omega_{31}t - \alpha_{13} + \phi_{12} + \phi_{23}) \Big\}, \end{aligned}$$

where $\alpha_{ij} = \arg V_{ij}$.

Figures (2) and (3) show an approximate locally optimal control, the (slowly-varying) profiles of its Bohr frequency components and the averaged and exact evolution of the three state system with $p = .9$ and $r = .1$, under this control for $T = 20\pi$. Figure (3), in particular, demonstrates the point we discussed in the introduction: The ‘averaged’ two-point boundary value problem is non-stiff because the short-time scale natural dynamics of the system has been averaged over and thus, its solutions are much easier to compute compared with those of the original two-point boundary value problem (I). In Appendix D, the special case with $p = 1$ is analyzed in detail and a complete solution to the optimal transfer problem (II) is given for that case.




Figure 2: Approximate optimal control for the transition $1 \rightarrow 3$ in $T = 20\pi$ and the corresponding frequency profiles.




Figure 3: Averaged (dashed lines) and exact (full lines) populations of the three-state system under the approximate optimal control.

Bound states of a Morse oscillator

Our final example considers the 22-dimensional space of bound states of the Morse oscillator model for the vibrational dynamics of the ground electronic state of the OH molecule. Here we solve the optimal transfer problem (II) numerically for two transfers, one from the ground vibrational state (state 1) to an intermediate excited vibrational state (state 10) and one from state 10 to the highest bound state, state 22. Figures (4) and (5) contain the state populations as well as the intensities (absolute values squared) of the frequency profiles as functions of rescaled time. Note the correspondence between high intensity value for a profile L_{ij} and the transition between states i and j .




Figure 4: Average populations and profile intensities vs. (scaled) time for a locally optimal transfer $1 \rightarrow 10$.

7 Conclusion

We examined the large transfer time limit of exact, optimal population transfers in a finite dimensional quantum system. The investigation of this problem uncovered useful structure in the optimal control and state trajectory and, moreover, resulted in the much simpler optimal control problem (II) whose solution provides the first order solution to the original optimal transfer problem, in a $\frac{1}{T}$ expansion. The main reason we considered *exact* population transfers is that in this case, the ‘average’ two-point boundary value problem (II) (equations (24) -




Figure 5: Average populations and profile intensities vs. (scaled) time for a locally optimal transfer $10 \rightarrow 22$.

(26)) is independent of the transfer time T of the original problem. This in turn allowed us to prove Theorems 2 and 3 which are important for uncovering the structure of solutions of optimal transfer problem (I). Moreover, an advantage of the optimal transfer problem (I) is that, once one has a solution to the ‘average’ two-point boundary value problem (II) one can derive from it approximate solutions to optimal transfer problem (I) *for all* transfer times T larger than some T_0 . On the other hand, solving the two-point boundary value problem (II) becomes extremely difficult as the dimension of the system grows. For practical applications to large-dimensional systems, an optimal transfer problem with an objective like (3)

$$a \int_0^T u^2(t) dt + \sum_{i=1}^N (|\psi_i(T)|^2 - p_i)^2,$$

which leads to *separated* boundary conditions would be preferable. Although an analog of Theorem (I) can be proven in this case too, it doesn’t seem so for Theorems 2 and 3. Yet, our technique of averaging over the short scale natural dynamics of the system would very much improve the efficiency of any method used for the solution of these problems, as well.

Appendix A

First, we prove the transversality conditions $\text{Im}(\psi_i^*(T) \lambda_i(T)) = 0$, $i = 1, \dots, N$. The optimal transfer problem (I) is a standard Bolza problem with (real) terminal state constraints, $|\psi_i(T)|^2 = p_i$, $i = 1, \dots, N$. According to the general theory of such problems [19], the transversality conditions for the costate at the final time are given by

$$\lambda_i(T) = \nu_i \frac{\partial(|\psi_i(T)|^2 - p_i)}{\partial \psi_i(T)^*} = \nu_i \psi_i(T), \quad (66)$$

where ν_i are the real Lagrange multipliers that enforce the terminal state constraints. The transversality conditions in the form we state them,

$$\text{Im}(\psi_i^*(T) \lambda_i(T)) = 0, \quad i = 1, \dots, N$$

follow easily.

Next, we prove that $\lambda(t)^* \psi(t) = 0$. One can easily show from equations (4) and (5) that $\lambda(t)^* \psi(t)$ is constant along any optimal trajectory and so, $\lambda(t)^* \psi(t) = \lambda(T)^* \psi(T)$. From the transversality conditions it follows that $\text{Im}(\psi^*(T) \lambda(T)) = 0$ and thus, $\text{Im}(\psi^*(t) \lambda(t)) = 0$. Let us now decompose λ as follows, $\lambda = c\psi + \lambda_\perp$, with c real and $\lambda_\perp$ perpendicular to ψ , i.e. $\lambda_\perp^* \psi = 0$. All we need to show is that $c = 0$. We introduce this representation of λ into equation (6). The resulting equation is

$$u = i(\lambda_\perp^* V \psi - \psi^* V \lambda_\perp) + i(c^* - c)(\psi^* V \psi),$$

and the reality of u forces c to be zero.

Appendix B

We prove that system (19) is controllable on account of the controllability assumption on the original system (1). Due to the fact that (19) has complex controls, every non-zero V_{ij} , $i \neq j$, provides us with two generators of $su(N)$ (traceless anti-Hermitian matrices), $E_{ij} - E_{ji}$ and $i(E_{ij} + E_{ji})$ (E_{ij} denotes a matrix with only one non-zero element, at the position (i, j) , equal to one. So, $(E_{ij})_{kl} = \delta_{ik}\delta_{jl}$). It is easy to see that $E_{ij}E_{mn} = \delta_{jm}E_{in}$. One can easily verify the following commutation relations:

$$[E_{ij} - E_{ji}, E_{jk} - E_{kj}] = E_{ik} - E_{ki}, \quad i \neq k, \quad (67)$$

$$E_{ij} - E_{ji}, i(E_{jk} + E_{kj}) = i(E_{ik} + E_{ki}), \quad i \neq k, \quad (68)$$

$$E_{ij} - E_{ji}, i(E_{ji} + E_{ij}) = 2i(E_{ii} - E_{jj}). \quad (69)$$

Due to the connectivity of the graph of V , there exists a sequence of index pairs that connects any state index i with any other state index j . Thus, starting with the given generators $E_{ij} - E_{ji}$ and $i(E_{ij} + E_{ji})$ for all $V_{ij} \neq 0$, $i \neq j$, we can generate, with repeated use of (67) and (68), all missing such generators

(corresponding to $V_{ij} = 0, i \neq j$). Finally, using (69) we can generate the diagonal generators of $su(N)$ (its Cartan subalgebra). For the system (61) which has real controls, every non-zero $V_{ij}, i \neq j$, provides us with a generator of $so(N)$ (anti-symmetric matrices), $E_{ij} - E_{ji}$. In that case, the repeated use of (67) is enough to establish controllability.

Appendix C

Here we show that the quadratic form

$$E(v) = \sum_{i \neq j}^N |V_{ij}|^2 |\psi_{0i} v_j^* - v_i \psi_{0j}^*|^2$$

in $v \in \{w \in \mathbb{C}^N \text{ s.t. } \psi_0^* w = 0\} \simeq \mathbb{C}^{N-1} \simeq \mathbb{R}^{2N-2}$ is positive definite, based on the connectivity of the graph of V . The non-negativity of E is obvious. Let $E(v) = 0$, then we have that

$$\psi_{0i} v_j^* - v_i \psi_{0j}^* = 0, \forall (i, j) \text{ s.t. } V_{ij} \neq 0. \quad (70)$$

Let us assume for a moment that $V_{12} \neq 0$. Then (recall, all $\psi_{0i} \neq 0$),

$$\frac{v_2}{\psi_{02}} = \frac{v_1^*}{\psi_{01}^*}.$$

It is straightforward to see that the connectivity of the graph of V and the repeated use of the relations (70) allows us to show that

$$\frac{v_i}{\psi_{0i}} = \frac{v_1}{\psi_{01}} \text{ or } \frac{v_1^*}{\psi_{01}^*}, \forall i = 2, \dots, N.$$

Recall now that both ψ_0 and v can be defined modulo global phases which we choose such that ψ_{01} and v_1 are real. Then,

$$\frac{v_i}{\psi_{0i}} = \frac{v_1}{\psi_{01}}, \forall i = 2, \dots, N.$$

The relation $\psi_0^* v = 0$ implies then that

$$\left(\sum_{i=1}^N |\psi_{0i}|^2 \right) \frac{v_1}{\psi_{01}} = 0,$$

which means that $v_1 = 0$ and hence $v = 0$.

Appendix D

In the special case $p = 1$, we can give a complete analytic solution to the optimal transfer problem (II) for the second example of section 6. The solution for the

matrix elements of L is given by

$$\begin{aligned} L_{12}(s) &= e^{i\phi_{12}} A \cos(ws), \\ L_{23}(s) &= -e^{i\phi_{23}} A \sin(ws), \\ L_{13}(s) &= e^{i(\phi_{12}+\phi_{23})} \frac{w}{1-r}, \end{aligned}$$

where w is determined to be $w = (2n+1)\frac{\pi}{2}$, $n \in \mathbb{N}$. To determine A , we have to solve the two-point boundary value problem given by (29),

$$\frac{d\bar{x}}{ds} = \begin{pmatrix} 0 & e^{i\phi_{12}} A \cos(ws) & e^{i(\phi_{12}+\phi_{23})} \frac{rw}{1-r} \\ -e^{-i\phi_{12}} A \cos(ws) & 0 & -e^{i\phi_{23}} A \sin(ws) \\ -e^{-i(\phi_{12}+\phi_{23})} \frac{rw}{1-r} & e^{-i\phi_{23}} A \sin(ws) & 0 \end{pmatrix} \bar{x},$$

and the boundary conditions

$$\bar{x}(0) = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix}, \quad \bar{x}(1) = \begin{pmatrix} 0 \\ 0 \\ e^{i*} \end{pmatrix}.$$

With the change of variables

$$y = \begin{pmatrix} y_1 \\ y_2 \\ y_3 \end{pmatrix} := \begin{pmatrix} \cos(ws) & 0 & \sin(ws) \\ 0 & 1 & 0 \\ -\sin(ws) & 0 & \cos(ws) \end{pmatrix} \begin{pmatrix} \bar{x}_1 \\ e^{i\phi_{12}} \bar{x}_2 \\ e^{i(\phi_{12}+\phi_{23})} \bar{x}_3 \end{pmatrix},$$

y satisfies the simpler equation

$$\frac{dy}{ds} = \begin{pmatrix} 0 & A & \frac{w}{1-r} \\ -A & 0 & 0 \\ -\frac{w}{1-r} & 0 & 0 \end{pmatrix} y.$$

The boundary conditions for $\bar{x}$ translate into the following conditions for y :

$$y(0) = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix}, \quad y(1) = \begin{pmatrix} \pm 1 \\ 0 \\ 0 \end{pmatrix}.$$

It is a straightforward calculation to find the solution for $y(s)$ and impose the boundary conditions. We find then that A must satisfy the condition

$$\cos \sqrt{A^2 + \frac{w^2}{(1-r)^2}} = \pm 1$$

which implies that

$$A = A(m, n) = \sqrt{(m\pi)^2 - \frac{w^2}{(1-r)^2}} = \pi \sqrt{m^2 - \frac{(n+1/2)^2}{(1-r)^2}},$$

where $m \in \mathbb{N}$ is such that $m \geq \frac{(n+1/2)}{(1-r)}$. The solution for the state evolution is given by

$$\begin{pmatrix} \bar{x}_1 \\ e^{i\phi_{12}} \bar{x}_2 \\ e^{i(\phi_{12}+\phi_{23})} \bar{x}_3 \end{pmatrix} (s) = \begin{pmatrix} \cos((n+\frac{1}{2})\pi s) & 0 & \sin((n+\frac{1}{2})\pi s) \\ 0 & 1 & 0 \\ -\sin((n+\frac{1}{2})\pi s) & 0 & \cos((n+\frac{1}{2})\pi s) \end{pmatrix} \begin{pmatrix} \cos(m\pi s) \\ -A(m, n) \frac{\sin(m\pi s)}{m\pi} \\ -\frac{n+1/2}{m(1-r)} \sin(m\pi s) \end{pmatrix}.$$

We see that the local minimizers for this optimal transfer problem are parameterized in terms of two integers, $n \in \mathbb{N}$ and $m \in \mathbb{N}$ such that $m \geq \frac{(n+1/2)}{(1-r)}$. The cost of such a minimizer can be easily computed to be equal to

$$J = 2\pi^2 \left[m^2 - \frac{(n+1/2)^2}{1-r} \right].$$

The values of m and n and the exact cost for the global minimum are uniquely specified by the value of r .

References

- [1] N. Khaneja, R. Brockett, and S. Glaser, “Time optimal control in spin systems,” *Physical Review A*, vol. 63, no. 032308, February 2001.
- [2] D. D’Alessandro, “The Optimal Control Problem on $so(4)$ and Its Applications to Quantum Control,” *IEEE Transactions on Automatic Control*, vol. 47, no. 1, January 2002.
- [3] N. Khaneja, T. Reiss, B. Luy, and S. Glaser, “Optimal control of spin dynamics in the presence of relaxation,” *arXiv:quant-ph/0208050*, 2002. Preprint.
- [4] D. D’Alessandro and M. Dahleh, “Optimal control of two-level quantum systems,” *IEEE Transactions on Automatic Control*, vol. 45, no. 1, June 2001.
- [5] U. Boscain, T. Chambrion, and J. Gauthier, “On the $k + p$ problem for a three-level quantum system: Optimality implies resonance,” *arXiv:math.OC/0204233*, April 2002. Preprint.
- [6] U. Boscain, T. Chambrion, J. Gauthier, S. Guérin, and H. Jauslin, “Optimal control in laser-induced population transfer for two- and three-level quantum systems,” *Journal of Mathematical Physics*, vol. 43, p. 2107, 2002.
- [7] L. Shen, S. Shi, and H. Rabitz, “Control of coherent wave functions: A linearized molecular dynamics view,” *Journal of Physical Chemistry*, no. 97, p. 8874, 1993.

- [8] V. Jurdjevic, "Hamiltonian point of view of non-Euclidean geometry and elliptic functions," *Systems & Control Letters*, no. 43, pp. 25–41, 2001.
- [9] A. Peirce, M. Dahleh, and H. Rabitz, "Optimal control of quantum-mechanical systems: Existence, numerical approximation, and applications," *Physical Review A*, vol. 37, no. 12, p. 4950, 1987.
- [10] W. Zhu and H. Rabitz, "A rapid monotonically convergent iteration algorithm for quantum optimal control over the expectation value of a positive definite operator," *Journal of Chemical Physics*, vol. 109, no. 2, p. 385, 1998.
- [11] S. Grivopoulos and B. Bamieh, "Iterative algorithms for optimal control of quantum systems," in *Proceedings of the 41st IEEE Conference on Decision and Control*, December 2002.
- [12] V. Ramakrishna, M. Salapaka, M. Dahleh, H. Rabitz, and A. Peirce, "Controllability of molecular systems," *Physical Review A*, vol. 51, no. 2, p. 960, 1995.
- [13] C. Altafini, "Controllability of quantum mechanical systems by root space decomposition of $\mathfrak{su}(N)$," *Journal of Mathematical Physics*, vol. 43, no. 5, p. 2051, 2002.
- [14] G. Turinici and H. Rabitz, "Quantum wavefunction controllability," *Journal of Chemical Physics*, vol. 267, p. 1, 2001.
- [15] V. Jurdjevic and H. Sussmann, "Control Systems on Lie Groups," *Journal of Differential Equations*, no. 12, p. 313, 1972.
- [16] R. Brockett, "System Theory on Group Manifolds and Coset Spaces," *SIAM Journal of Control*, vol. 10, no. 2, p. 265, 1972.
- [17] R. Brockett, "Lie Theory and Control Systems defined on Spheres," *SIAM Journal of Applied Mathematics*, vol. 25, no. 2, p. 213, 1973.
- [18] V. Jurdjevic, *Geometric control theory*. Cambridge University Press, 1997.
- [19] A. P. Sage and C. C. White, III, *Optimum Systems Control*. Prentice-Hall, second ed., 1977.
- [20] U. Boscain and G. Charlot, "Resonance of minimizers for n-level quantum systems with an arbitrary cost," *arXiv:quant-ph/0308103*, August 2003. Preprint.
- [21] H. Khalil, *Nonlinear Systems*. Prentice Hall, second ed., 1996.
- [22] V. Arnol'd, *Ordinary Differential Equations*. Cambridge, MIT Press, 1973.